

# 18x5in1 LED Par Light

## Panel operation

MENU: select function mode, or return to the previous menu

UP: Select upward

DOWN: select down

ENTER: Confirm selection

main menu	Adjustable range	Remark
d001	001-512	address code
CHAL	CH5/CH9	Channel selection
CC50	01-99	Program jump
DE50	01-99	Procedural gradient
CP50	01-99	Procedural changes
SU99	01-99	Voice control
R255	000-255	red dimming
G255	000-255	green dimming
B255	000-255	blue dimming
W255	000-255	white dimming
A255	000-255	yellow dimming

Channel 5	Channel value	Function description
CH1	0-255	red dimming
CH2	0-255	green dimming
CH3	0-255	blue dimming
CH4	0-255	white dimming
CH5	0-255	yellow dimming

Channel 9	Channel value	Function description
CH1	0-255	Total dimming
CH2	0-255	red dimming
CH3	0-255	green dimming
CH4	0-255	blue dimming
CH5	0-255	white dimming
CH6	0-255	yellow dimming
CH7	0-255	Strobe
CH8	0-255	50-255 Turn on the macro function, voice control
CH9	0-255	slow to fast, and the sound control sensitivity is from slow to fast