

# RGBW LED Matrix COB Beam 36x15W 4in1 Blinder Manual

## Panel operation



Menu: Select the function mode, or return to the previous menu menu  
 Up: choose upward  
 Down: select downward  
 Enter: Confirmation Selection

main menu	Sub -menu 1	Sub -menu 12	Remark
Addr	D001/D512		address code
CHAL	CH10/CH41/C144/C154		aisle
AUTO	CA50	01-50	
	CB50	01-50	
	CC50	01-50	
	CD50	01-50	
	CE50	01-50	
	CF50	01-50	
	CG50	01-50	
	CH50	01-50	
	CJ50	01-50	
	...		
ES	01-50		
AUTO			Self -walking and speed
SOUD	SO01-SO99		Sound control mode
STAT	c000	c000-0255	Operating mode, a total of 127 operating effects
	r000	r000-r255	Red manual lighting
	g000	g000-g255	Green manual lighting
	b000	b000-b255	Blue manual lighting
	W000	W000-b255	White manual lighting
	t000	t000-t255	Flash
Rest	On/Off		reset

CH10	dmx channel value	basic Function
1	000-255	Always lit
2	000-255	Flash
3	000-255	R red lamp beads light
4	000-255	G green lamp beads light
5	000-255	B blue lamp beads light
6	000-255	W blue lamp beads light
7	000-255	Letter and letters
8	000-255	Prospect color selection
9	000-249	Macro
	250-255	Sound control
10	000-255	Macro self-walking speed (0-127 from fast to slow, 128-255 from right to fast)

CH41	dmx channel value	basic Function
1	000-255	Red total light
2	000-255	Green total light
3	000-255	Blue Total Light
4	000-255	White Total Light
5	000-255	Flash
6	000-255	Light beads 1st
...	...	...
41	000-255	The 36th lamp beads light

CH144	dmx channel value	basic Function
1	000-255	R's 1st red lamp bead linear lighting
2	000-255	G of the first green lamp beads linear lighting
3	000-255	B the first blue lamp beads linear light tone
4	000-255	W the first blue lamp bead linear lighting
...	...	...
141	000-255	R's 36th red lamp beads linear light tone
142	000-255	G's 36th green lamp beads linear light tone
143	000-255	B the 36th blue lamp beads linear light adjustment
144	000-255	W the 36th blue lamp beads linear light tone

CH154	dmx channel value	basic Function
1	000-255	Always lit
2	000-255	Flash
3	000-255	R red lamp beads light
4	000-255	G green lamp beads light
5	000-255	B blue lamp beads light
6	000-255	W blue lamp beads light
7	000-255	Letter and letters
8	000-255	Prospect color selection
9	000-249	Macro
	250-255	Sound control
10	000-255	Macro self-walking speed (0-127 from fast to slow, 128-255 from right to fast)
11	000-255	R's 1st red lamp bead linear lighting
12	000-255	G of the first green lamp beads linear lighting
13	000-255	B the first blue lamp beads linear light tone
14	000-255	W the first blue lamp bead linear lighting
...	...	...
152	000-255	R's 36th red lamp beads linear light tone
152	000-255	R's 36th red lamp beads linear light tone
153	000-255	G's 36th green lamp beads linear light tone
154	000-255	W the 36th blue lamp beads linear light tone