

200W led COB Par light

main menu	Adjustable range	Remark
d001	001-512	address code
CHAL	CH2/CH6	Channel selection
CC50	01-99	Program jump
DE50	01-99	Procedural gradient
CP50	01-99	Procedural changes
SU99	01-99	Voice control
R255	000-255	Cold white dimming
G255	000-255	Warm White dimming

Channel 2	Channel value	Function description
CH1	0-255	Cold white dimming
CH2	0-255	Warm White dimming
Channel 6	Channel value	Function description
CH1	0-255	Total dimming
CH2	0-255	Cold white dimming
CH3	0-255	Warm White dimming
CH4	0-255	Strobe
CH5	0-255	50-255 Turn on the macro function, voice control
CH6	0-255	The program speed is from slow to fast, and the sound control sensitivity is from slow to fast